

PCT-610/620

interM

PUBLIC ADDRESS AMPLIFIER



FEATURES

- ONE CHANNEL FULL DIGITAL AMPLIFIER
120W, 240W(High/Low impedance, 70V/100V/4Ω)
- 6 Balanced XLR inputs with sensitivity controls
- Digital 3 Band Equalizer on 6 XLR input
- 1CD Player(MP3/WMA), Slot-In Type Reliable Mechanism
- Digital FM Tuner
- Dot MATRIX design VFD Display
- Switchable audio signal priority override on channels 1 & 2(overrides defeat all music modules and channels 3, 4, 5 & 6)
- EM broadcasting stored in DRP IC is outputted
- Convenient 4 tone chime for use with announcements - local and remote operation
- Tel in, Music on Hold, EXT chime, EXT Mute function
- Switchable Phantom Power on each input
- 5 Local speaker selectors
- REMOTE CONTROL INPUT
Individual speaker zones can be selected and chime can be operated by wired remote control(RM-05A)
- RS-232C Serial port for AMX or Crestron interface.
- IR remote control function

SPECIFICATIONS

- ELECTRICAL *0dB=0.775Vrms
 - Rated Output Power.....PCT-610:120W (RMS)
(<THD 1%, AES17 Filter) PCT-620:240W (RMS)
 - Frequency Response.....80Hz~20kHz
 - SNR(Mic).....Better than 65dB
 - Input Sensitivity/Impedance
 - CH1~CH6.....1mV~160mV/600Ω
 - Aux In.....300mV/10kΩ
 - Telephone In/Impedance.....0.775V/600Ω
 - Remote In/Impedance1mV~160mV/600
 - Pre-amp Out/Impedance.....1V/600
 - Music on Hold/Impedance.....0.775V/600
 - Aux Out/Impedance500mV/600
 - Tone Control(100Hz, 10kHz)±8dB
 - EQ Control(150Hz, 1kHz, 10kHz).....±8dB
- GENERAL
 - Power Source100~120VAC or 220~240VAC; 50/60Hz
(supplied AC mains transformer depends on local requirements)
 - Power ConsumptionPCT-610:70W, PCT-620:100W
 - WeightPCT-610:8.5kg/19lb, PCT-620:9.5kg/21lb
 - Dimensions.....482(W)x132(H)x380(D) mm
19(W)x5.2(H)x14.9(D)in

interM

OFFICE : 653-5 BANGHAK-DONG, DOBONG-KU, SEOUL, KOREA TEL : 82-2-2289-8140~8, FAX : 82-2-2289-8149

Home page : <http://www.inter-m.com>

E-mail : export@inter-m.com

9027104900