

MIC WITH ZINE CONTROL FOR PAM-SERIES MIXER/AMPLIFIERS



FEATURES

- SINGLE SHOT CHIME
- SPEAKER LINE CONTROL
Speaker zone of PAM-240A/360A can be control by RM-05A.
- ZONE CONTROL CIRCUITS
Speaker zones can be selected individually by means of the CHANNEL switches or altogether using the ALL CALL switch.
- ANNOUNCEMENTS BY MICROPHONE
Unobtrusive and easy to use condenser type microphone which is highly sensitive and reproduces high clarity speech.
- PRE-ANNOUNCEMENT CHIME
A four tone chime is incorporated for pre-announcement purposes. It is initiated by pressing the CHIME switch.
- LED OUTPUT LEVEL INDICATION
The ten segment LED barograph display indicates the instantaneous signal output level of the amplifier.

SPECIFICATIONS

- ELECTRICAL * 0dB=0.775Vrms
 - Output Level/Impedance+4dB(unit gain)/600Ω, BAL
 - MIC Input Sensitivity/Impedance-50dB/600Ω, BAL
 - Frequency Response20Hz~20kHz, -3dB
 - THDLess than 0.1%
 - S/NBetter than 65dB
 - Speaker Control Terminal & Switch5CH
- MIC (CMC-01) SPECIFICATIONS
 - TypeCondenser Microphone
 - Polar PatternUnidirectional
 - Frequency Response100Hz~16,000Hz
 - ImpedanceMax 680Ω
 - Sensitivity(0dB=1V/0.1Pa at 1kHz)-47dB±3dB
 - Sensitivity ReductionWith in -3dB at 1.0V
 - Current ConsumptionMax 0.5mA
 - S/N RatioMore than 60dB
 - Standard Power SupplyDC 1.5V
 - Weight Goose Neck200g
- GENERAL
 - Power SourceDC 24V(used by D-Sub connector)
 - Weight.....900g / 2lb(Without Microphone)
 - Dimensions194(W)x60.4(H)x205(D)mm
7.6(W)x2.3(H)x8(D)in